

# LED FLAT PAR CAN TRI 3W

## DMX CONTROL TABLE



2-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0-100%)
CH2	000 - 255	Colour macro
	000 - 036	Red
	037 - 073	Green
	074 - 110	Blue
	111 - 147	Yellow
	148 - 184	Magenta
	185 - 221	Cyan
	222 - 255	White

3-CHANNEL MODE 1		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0-100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 004	Blackout
	005 - 080	Colour macro (red, green, blue, yellow, magenta, cyan, white)
	081 - 150	Colour change (rate)
	151 - 220	Colour blending (rate)
	221 - 255	Music control (microphone sensitivity)

3-CHANNEL MODE 2		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Red (0 - 100%)
CH2	000 - 255	Green (0 - 100%)
CH3	000 - 255	Blue (0 - 100%)

<b>6-CHANNEL MODE</b>		
<b>CHANNEL</b>	<b>VALUE</b>	<b>FUNCTION</b>
CH1	000 - 255	Master dimmer (0-100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 225	Red (0 - 100%)
CH4	000 - 225	Green (0 - 100%)
CH5	000 - 225	Blue (0 - 100%)
CH6	000 - 004	Blackout
	005 - 080	Colour macro (red, green, blue, yellow, magenta, cyan, white)
	081 - 150	Colour change (rate)
	151 - 220	Colour blending (rate)
	221 - 255	Music control (microphone sensitivity)